

表一六三之八～二 以馬力及電壓額定選用隔離設備及操作器之三相堵轉電流轉換表

電壓 額定 馬力	三相電動機最大堵轉電流(安培)							
	115 伏	200 伏	208 伏	220 伏	230 伏	380 伏	460 伏	575 伏
1/2	40	23	22.1	20.9	20	12	10	8
3/4	50	28.8	27.6	26.1	25	15	12.5	10
1	60	34.5	33	31	30	18	15	12
1 1/2	80	46	44	42	40	24	20	16
2	100	57.5	55	52	50	30	25	20
3	—	73.6	71	67	64	39	32	25.6
5	—	105.8	102	96	92	56	46	36.8
7 1/2	—	146	140	132	127	77	63.5	50.8
10	—	186.3	179	169	162	98	81	64.8
15	—	267	257	243	232	141	116	93
20	—	334	321	303	290	176	145	116
25	—	420	404	382	365	221	183	146
30	—	500	481	455	435	263	218	174
40	—	667	641	606	580	351	290	232
50	—	834	802	758	725	439	363	290
60	—	1001	962	910	870	527	435	348
75	—	1248	1200	1135	1085	657	543	434
100	—	1668	1603	1516	1450	878	725	580
125	—	2087	2007	1898	1815	1098	908	726
150	—	2496	2400	2269	2170	1314	1085	868
200	—	3335	3207	3032	2900	1755	1450	1160
250	—	—	—	—	—	—	1825	1460
300	—	—	—	—	—	—	2200	1760
350	—	—	—	—	—	—	2550	2040
400	—	—	—	—	—	—	2900	2320
450	—	—	—	—	—	—	3250	2600
500	—	—	—	—	—	—	3625	2900